



Punch Marine 500 Watt 2-Channel Amplifier

Regular Price £737.26 Special

Price

£516.08

Excl. Tax: £430.07

Product Images

















Short Description

The PM500X2 is a 500 Watt 2-channel amplifier with high dynamic power using Class-a/b technology and a conformal coated pc board designed for motorsport and marine applications.

Description

The PM500X2 is an excellent way to PUNCH up your sound system without monopolizing your entire trunk - that way you have more room for subs! With its massive output stage, this amplifier is best suited for driving

a pair of 8-ohm SVC subwoofers or four 2-ohm DVC subwoofers. Remember to utilize the recommended power and speaker cables to optimize power delivery.

- High level input capable with Auto Turn-On circuit
- RCA pass-thru outputs
- Features C.L.E.A.N. Set-up
- Optional remote Punch Level Control (PLC2) ready (w/ input clip indicator)
- 12dB/octave Butterworth crossover
- On-board Punch EQ with +18dB boost @ 45Hz
- Muted turn on
- Stealth top mounted control panel
- Cast aluminum heatsink
- Short circuit protection
- Over current protection
- Marine grade 2-part epoxy coated PCB
- Marine grade stainless steel hardware
- 2-Year Warranty

Additional Information

| Weight (kg) | 4.900000 |
|------------------------------------|--|
| Manufacturer | Rockford Fosgate |
| Finish | Anodised Aluminium |
| Number of Channels | 2 |
| Total Power (Sum of Rated Power) | 500 Watts |
| Rated Power (RMS Continuous Power) | 150 Watts x 2 @ 4-Ohm 250 Watts x 2 @ 2-Ohm 500 Watts x 1 @ 4-Ohm Bridged |
| Bridgeable | Yes Terminals: Left (+) Right (-) |
| Input Sensitivity | 150 mV to 12 V |
| Speaker Outputs | No |
| Power Output | CEA-2006 Power Rating 150W x 2 @ 4Ω ≤1.0% THD+N |
| Circuit Topology Class | Class A/B |
| Efficiency | 73% @ 4-Ohm |
| Signal Input | Hi/Low level: 1 RCA pair |
| Tone Controls | Bass: 0dB to +18dB @ 45Hz and/or Treble: 0dB to +12dB @ 12.5kHz Function depends upon LP/AP/HP switch position |
| Crossover Controls | High-Pass: 50Hz-250Hz @ 12dB/Octave Butterworth Low-Pass: 50Hz-250Hz @ 12dB/Octave Butterworth All- Pass: Yes |
| Visual Indicators | Power/Protect/Thermal LED Input Clip LED3 Output Clip LED1,2,3 LED Color Legend: 1BLUE: <0.5% THD 2VIOLET: 1% THD 3RED: 10%+ THD |
| Power Wire Gauge | 4 AWG |
| Power Input Connector | Captive C-Clamp |
| Speaker Wire Gauge | 8 AWG to 18 AWG |
| Speaker Output Connector | Captive C-Clamp |
| Cooling | Convection |
| Fuse | 80 Amps |
| | |

| Steering Wheel Control Ready | No |
|-----------------------------------|--|
| Multi-Function Display Compatible | No |
| Sirius XM Ready® | No |
| iPod / iPhone Compatible | No |
| AUX Input | No |
| Pandora Internet Radio | No |
| Clock | No |
| Input Voltage | 9 - 16 Vdc |
| Compatible Remotes | Optional PLC2 provides Punch Level Control |

