



Punch Marine AM/FM/WB Digital Media Receiver 2.7" Display w/ CAN bus 2 Zone

E775.28 Special Price
£542.70

Excl. Tax: £452.25

Product Images









Short Description

The PMX-5 is an AM/FM/WP tuner and compact digital media receiver with a 2.7" full colour display and CAN bus functionality. This media source unit features 2 zone / 2 source technology allowing you to have 2 separate zones listening to 2 separate music sources. The built-in amplifier is able to power 1 zone, an additional amplifier is required for the second zone.

Features CANbus functionality for connection to Raymarine, Garmin and other MFD (Multi-Function Display) systems using PMX-CAN.

Description

The PMX-5CAN digital media receiver is designed for marine and motorsports systems.

The PMX-5CAN features a 2.7"full color TFT display for optimum viewing - even in full sun - that is optically wet bonded to prevent any dust or moisture penetration. It is IPX6 rated and uses a water resistant rotary encoder knob with white LED button illumination and front mounted sub level controls. Additionally, with features such as SiriusXM and Pandora capabilities, Bluetooth audio steaming with album art support for Apple and Android products and true 2 zone/2 source control, this unit becomes a true command center of any system.

Output flexibility comes a 4x50W @ 20hm internal amplifier or dual zone output RCA's allowing the addition of after-market amplifiers for more power and output. Add in the EEPROM memory system, custom GUI interface and wired remote expansion capabilities and you have the only media receiver you'll ever need. The PMX-5CAN also features CANbus functionality for connection to Raymarine MFD (Multi-Function Display) systems using the PMX-CAN adaptor (see Accessories tab.)

- ISO8846/SAE J1171 Ignition Protection Certified
- Stainless Steel Rear Chassis
- Steering Wheel Control Interface Compatible
- Pandora Internet Radio
- SiriusXM-Ready™
- A2DP and AVRCP Bluetooth Wireless Streaming
- FCC, CE, IC, and C-Tick Certified
- Multi Region Radio Frequencies
- Low Voltage Warning Alert
- AUX and USB Inputs with USB Charging
- On Board Punch EQ Control
- Independent Subwoofer Level Control
- Selectable HP / LP / AP Crossovers with Selectable Slope 12 / 24 dB/Oct
- IPX6 Marine Grade
- 7-Band Graphic EQ
- 2.7" full color display w/ auto dimming backlightning
- Zone Control: 2 Zone / 2 Source (F/R/S + F)
- AM / FM / WB Tuner
- CANbus (Controller Area Network) compatible. Requires PMX-CAN accessory
- Compatible with a Multi-Funtion Display using NMEA2K entertainment standard. See our MFD Compatibility Chart
- *Antenna not included
- 2-Year Warranty

Additional Information

Weight (kg)	2.270000
Manufacturer	Rockford Fosgate
Finish	Black
Display Size	2.7" Colour TFT
FM Tuner Frequency Range	87.5 MHz - 107.9 MHz
FM Tuner Sensitivity	8 dB
AM Tuner Frequency Range	530 kHz - 1710 kHz
AM Tuner Usable Sensitivity	40 dB
Tuner Number Of Presets	18 FM / 12 AM / 6 WB
Speaker Impedance	2-Ohms
Speaker Outputs	Yes
Power Output	CEA-2006 Power Rating 25W x 4 @ 4Ω RMS 50W x 4 @ 2Ω Peak ≤1.0% THD+N
USB Version	2.0
USB Capacity	32Gb max. 999 Folders max. 999 Songs max.
USB Output Current	1A
Fuse	15 Amps
Steering Wheel Control Ready	Yes
Multi-Function Display Compatible	Yes
Android Compatibility	Bluetooth® Only
Sirius XM Ready®	Yes
iPod / iPhone Compatible	Yes
AUX Input	Yes
Media Player Audio Format Compatibility	MP3, WMA
Multi-Zone / Multi-Source	2 Zone / 2 Source
Pandora Internet Radio	Yes

Clock	No
Input Voltage	10.5Vdc - 16Vdc
IP Rating	IPX6
Cut-out Size (mm)	51.00 x 180.00
Depth (mm)	182.00
Compatible Remotes	PMX-1R, PMX-0R
RCA Output Impedance	500Ω
RCA Output Voltage	2V RMS Does not clip at full output
RCA Outputs	(1 pair) Front (1 pair) Rear (or Sub-out)

